

RadEye PX

Survey Meter for External Proportional Probes



Key Features and Benefits

- The RadEye PX can operate with proportional counter tubes
- Up to 16 different probe configurations are selectable in a submenu
- Easy to replace probes in-the-field, with a simple button-push
- Weighs only 160 g (5.6 oz) with rubber protection, without cable, 110 x 67 x 62 mm (4.3" x 2.6" x 2.4")
- Traditional probes can be used for one and two hand operation
- Versatile operation modes
- RadEye BTcom cover for Bluetooth® communication

The RadEye PX is a modern and compact multi-purpose meter for external proportional counter tubes.

The RadEye PX is a modern compact multi-purpose survey meter for proportional counter tubes. General count rate and surface contamination measurements can be performed as well as dose rate measurements, typically with He-3 or BF₃ based Rem-counters.

As part of the growing RadEye product family of high-end stand-alone meters, the RadEye PX is designed to exceed the most demanding user expectations.

Due to the clear and large display all essential functions and software parameters can be easily accessed. The display and the alarm-LED can be seen while the instrument is worn in the transparent case.

All settings and the data analysis can be done by an optional Windows™-based PC-software and a reader device. The last 1500 mean and maximum values of the count rate or dose rate are recorded internally and can be read out via a serial interface. Additionally the RadEye PX logs the last 250 alarms, error messages and changes of the configuration.

Operation modes:

- Scaler / Timer with preset count and preset time for sample measurements
- Continuous ratemeter mode for frisker operation
- Simultaneous α / β and gross / ROI operation (distinct audible indication for each measuring channel)



Options and Specifications

RadEye PX Specifications


Measured quantities	Count rate (cps, cpm), surface contamination (Bq, dps, dpm, Bq/cm ²), dose rate (R/h, Sv/h, rem/h).
Background subtraction	In count rate and contamination mode.
Measuring range	Default: 100,000 cps - extendable by individual probe calibration.
Probe cables	RG 58, max. 1.5 m (59") – MHV connector.
High voltage range	100 V...2300 V with output impedance 2 MΩ.
Probe library	16 different detectors with corresponding high voltage, calibration factor, dead time correction, overload threshold, detector area and timeout for detector failure.
Alarm threshold	Two alarm thresholds for count rate, activity, dose and dose rate each.
Audible alarm intensity	80 dB at a distance of 30 cm (11.8").
Working temperature	-20°C ... + 50°C (-4°F ... 122°F).
Relative humidity	10 ... 90 % at 35°C (95°F) not condensing.
Operating voltage	1,8 ... 4 V, battery low voltage starting from 2.3 V.
Scaler/Timer	Preset count, preset time.
EMC	Disturbance emission: EN 61000-6-3, Immunity: EN 61000-6-2.
Size	110 mm x 67 mm x 62 mm (4.3" x 2.6" x 2.4"), with rubber protection, without cable.
Weight	Around 160 g (5.6 oz) including AAA cells and protection sleeve.
Internal memory	The last 1500 measured values are saved and can be read out via PC program. Max and mean value of count rate and dose rate. The time interval is factory preset to 120 s by default. As well scaler measurements and momentaneous readings can be stored manually. Logbook with 250 entries for changes of configuration, occurring alarms and errors.
Averaging filters	Ratemeter filter type: Advanced Digital Filter (ADF), Digital RC-Filter with time constant, 1s...180 s, depending on count rate and count rate change.
Battery life time	Approx. 200 h.

RadEye PX Accessories

Transparent case with lanyard
425067044



The RadEye BTcom cover with manual and RadEye.exe update installation file
425067087



Probe cables MHV to MHV, SHV to MHV and MHV to PET, various lengths available



Right-angle-plug converter
KT 162245107



RadEye PX adapter for NRD
425069501



RadEye PX adapter for Wendi
425069460



Battery lid # 425067034 for inductive chargers



Desktop holder and inductive charger # 425067083

